## **50A/100A SMALL SPLIT CORE CURRENT TRANSFORMERS**



Split-core current transformers provide linear output voltage that is directly proportional to the input current. These transformers are safely and easily installed over existing electrical power lines without disconnecting the lines or interrupting service.

DENT's energy monitoring components are used for a variety of applications including building automation, tenant submetering, performance verification, energy management, and new technology assessment.

KEY SPECIFICATIONS					
Window Size	0.75" (1.90 cm)				
Current Range	50A Model: 5 - 65A AC 100A Model: 2 - 130A AC				
Output	333 mV at rated current				
Ratio Error	<1% at rated current (typical)				
Phase Error	<2° at rated current (typical)				



AMP

## **ELECTRICAL** Output

Wire Polarity

333 mV at rated current White = Hi, positive (+) Black = Low, negative (-)

50 to 400 Hz Frequency Range

**MECHANICAL** 

Case Material Epoxy encapsulated housing Leads 2.7 M (8'), twisted pair, 20 AWG

**Operating Temperature** -20° to 55°C (-4° to 131°F)

## **SAFETY**

Working Voltage 600 VAC, Category III Dielectric Strength 5000 VAC around case 600V rated leads Certification Conforms to: UL STD 61010-1


Intertek 3101607

EN 60044-1 Certified to: CAN/CSA STD C22.2 No. 61010-1

## **PART NUMBERS**

CT-SCS-0050-U/B 50A Small Split Core CT-SCS-0100-U/B 100A Small Split Core

DENT P/N	NOMINAL RATING (Amps)	USEFUL CURRENT RANGE (Amps)	DIMENSIONS				
			A	В	С	D	Е
CT-SCS-0050 CT-SCS-0100	50 100	5 - 65 2 - 130	5.08 cm (2.0")	5.34 cm (2.1")	1.55 cm (0.6")	1.90 cm (0.75")	1.90 cm (0.75")



All specifications contained in this document are subject to change without notice. © DENT INSTRUMENTS, INC.