

# POWERXPLORER PX5

## SPECIFICATIONS

### Measured Parameters

(4) differential voltage inputs, 1-600 Vrms, AC/DC, 0.1% rdg + 0.05% FS, 256 samples/cycle, 16 bit ADC  
 (4) current inputs with CTs 1-6000 Arms CT-dependent, AC/DC, 0.1% rdg + CTs, 256 samples/cycle, 16 bit ADC  
 1 MHz High Speed Sampling, 14 bit ADC  
 Frequency Range, 10 mHz resolution, 15-20 Hz, 45-65 Hz  
 Phase Lock Loop - Generator tracking, Standard PQ mode

### Monitoring/Compliance

IEEE 1159  
 IEC 61000-4-30 Class A  
 EN50160 Quality of Supply  
 Current Inrush/Energization  
 Voltage Fault Recording  
 Long Term Monitoring w/min/max/avg  
 Continuous Data Logging

### Power Quality Triggers

Cycle-by-cycle analysis  
 256 samples/cycle; 1/2 cycle RMS steps  
 L-L, L-N, N-G RMS Variations: Sags/swells/interruptions  
 RMS Recordings V & I (32 pre-fault, 10K post-fault cycles)  
 Waveshape Recordings (32 pre-fault, 10K post-fault cycles)  
 Low and Medium Frequency Transients - V & I  
 High Frequency Transients - V & I, 3% FS trigger  
 Harmonics Summary Parameters  
 Cross trigger V & I channels  
 RMS Event Characterization (IEEE or IEC)  
 Transient Event Characterization

### Distortion/Power/Energy

W, VA, VAR, TPF, DPF, Demand, Energy, etc.  
 IEEE 1459 Parameters of distorted and unbalanced  
 Harmonics/Interharmonics per IEC 61000-4-7  
 THD/Harmonic Spectrum (V,I,W) to 63rd  
 TID/Interharmonic Spectrum (V,I) to 63rd  
 Flicker per IEC 61000-4-15 (Pst,Plt,Sliding Plt)  
 Crest Factor, K Factor, Transformer Derating Factor,  
 Telephone Interference Factor  
 Unbalance (max rms deviation) & sequencing components  
 5 User Spec Harmonics or Signaling Frequency  
 Vector/Arithmetic/Coincident Parameters

### Available Languages

English, Spanish, French, German, Italian, Swedish, Finnish, Chinese, Japanese, Korean

### General Specifications

Size (HxWxD): 12" x 2.5" x 8" (30cm x 6.4cm x 20.3cm)  
 Weight: 4.2 pounds (1.9 kg)  
 Operating Temperature: 0° to 50° C (32° to 122° F)  
 Storage Temperature: -20° to 55° C (4° to 131° F)  
 Humidity: 10 to 90% non-condensing  
 System Time Clock-Crystal controlled-1 second resolution  
 Charger/Battery Eliminator: 90-264 VAC 47-63 Hz  
 Display: LCD color touch screen  
 Removable Memory: Compact Flash, up to 32GB, 4GB min.

### Optional Accessories

Current Probes: An extensive selection, including:  
 Model TR-2510A 1-10 A; up to 0.47" conductors  
 Model TR-2500A 10-500 A; up to 1/8" diameter or 2.5" x 0.2" conductors  
 Model TR-2520A 300-3000 A; up to 2.56" diameter or 1.97" x 5.3" (bus bar)  
 Flexible Current Probes  
 DRANFLEX3000XL/24/36/48; 30/300/3000A available in 24", 36", 48"  
 Hall Effect Probes for AC/DC applications, 150 A or 1500 A  
 CT Cable Adapter (CA4300BNC)  
 Voltage Cable Accessory Pack (VCP4300)  
 Soft Carrying Case (SCC-4300)  
 Field Replaceable Battery Pack (BP-PX5)  
 External Battery Charger (XBC-PX5)  
 Reusable Shipping Container (RSC-4300)  
 Weather Resistant Container (ENCL-HH)  
 Lockable Portable Case (LPC-PX5)  
 Communications Interface (Includes NodeLink®):  
 RS232 FiberOptic Adapter (COMM-RS232)  
 USB FiberOptic Adapter (COMM-OUA)  
 LAN-FiberOptic Adapter (COMM-OEA)  
 DranView software: Runs under Windows 98, ME, NT, XP, Vista, 7  
 CD-ROM Training Program

**DRANETZ**™ 1.800.372.6832 sales@dranetz.com

dranetz.com

tel 732.287.3680 • fax 732.248.1834 • 1000 New Durham Road • Edison, New Jersey 08818 USA  
 PowerXplorer, NodeLink and DRAN-VIEW are trademarks of Dranetz. ©2010 Dranetz. All rights reserved.  
 Printed in the United States. Specifications are subject to change without notice.



Shop for Power Metering products online at: [www.PowerMeterStore.ca](http://www.PowerMeterStore.ca) 1.800.561.8187

# POWERXPLORER

# PX5

## Power Quality Analyzer



**DRANETZ**™  
[www.dranetz.com](http://www.dranetz.com)


*Sets the new standard for high performance,  
 advanced measurement capabilities  
 and enhanced usability*

**DRANETZ**™  
[www.dranetz.com](http://www.dranetz.com)

The PowerXplorer™ PX5 integrates the most advanced feature set available in a power monitoring instrument, with an easy-to-navigate, color graphical user interface. With high-speed sampling and data capture (1 microsecond/channel), this 8-channel workhorse simultaneously captures and characterizes hundreds of parameters, using a range of standard and customizable operating modes. The unique measurement capabilities of the PowerXplorer include capture of low-medium-high frequency transients through peak, waveshape, rms duration and adaptive high-speed sampling, as well as power measurements to clearly characterize non-sinusoidal and unbalanced systems.


#### Power Quality Surveys and Diagnostics

A power quality survey is key to pinpointing and diagnosing problems or negative trends and to effectively implement a reliability-centered maintenance program. By evaluating power quality over a week or longer, baseline conditions and susceptibility to events can be determined so that corrective measures can be implemented. The PowerXplorer has a built-in event characterizer that directly supports troubleshooting and the gathering of survey data—for improving power quality and equipment reliability, as well as for matching the requirements and susceptibilities of that equipment to the incoming supply.




#### Fast Transient Capture

The PowerXplorer uses digitized high-speed sampling to capture and analyze microsecond-wide transients (Dranetz 658-like and BMI 8800-like). Transients, generated by fast-switching electronics, medical diagnostic equipment, capacitor switching, lightning, transformer energization, and load shifting, are immediately characterized as impulsive or oscillatory and detailed for further analysis. Capable of capturing the complete power quality spectrum, the PowerXplorer provides scope-like display of the entire transient.




#### Load Distortion and Imbalance

Rectified-input power supplies plus other non-linear loads have increased from 25% of the total U.S. load to over 65% today. These loads draw current only during part of the waveform, resulting in current distortion, and depending on harmonic impedances, which causes voltage distortion as well. This distortion can have a significant derating effect on equipment such as motors and transformers, causing overheating that shorten equipment life. The PowerXplorer measures the full range of arithmetic, vector and sequencing parameters contained in IEEE 1459, to evaluate distortion and restore balanced loads.




# POWERXPLORER

# PX5





#### Flicker

The activation of arc furnace, large induction machines and other large loads that produce continuous voltage impulses cause a power quality event called flicker. Typically, flicker occurs on systems that are weak relative to the amount of power required by the load, combined with considerable variations in current occurring over a short period of time. The PowerXplorer captures flicker data per IEC 61000-4-15, which can be further evaluated using DranView visualization, analysis and reporting software.




#### Compliance Monitoring

The PowerXplorer has been designed to meet the most advanced power quality standards, including IEEE 1159, IEC 61000-4-30 and EN50160. A statistical output is produced to quickly verify compliance with international quality-of-supply standards and benchmark power quality. In an instant, the PowerXplorer provides a snapshot of over 13 key parameters, including unbalance, voltage variations and harmonics.



DranView is a powerful, yet simple to use tool to visualize and analyze complex power quality events, locate faults, isolate potentially harmful trends, and correlate data among and across sites.

PowerXplorer users can select from a multitude of data displays such as phasors, waveforms, meters and harmonic spectrums, as well as recording options that include continuous monitoring or report-by exception, and AC and DC measurements for events lasting from a microsecond to an hour. Information presentation options range from quality-of-supply, statistical and trending to the PowerXplorer's unique annunciator "report card" that provides instant classification of events. Remote communications are made easy using RS-232, ethernet or USB options to download data for further analysis and reporting using industry-leading DranView software.



Provides information about the type and severity of the sag and indicates the direction of the sag relative to the monitoring point.

To further speed analysis, Dranetz provides AnswerModules®, intelligent algorithms that help pinpoint the source and cause of power quality problems to the PowerXplorer PX5. These diagnostic and reporting tools are based on decades of analytical experience and benchmarking/troubleshooting work, as they convert raw data into precise answers for rapid decision-making.

#### Harmonics

As the sensitivity of power electronics increases, equipment ranging from HVAC systems, personal computers and copiers to computerized process equipment and manufacturing systems are susceptible to harmonic pollution. In fact, harmonics can cause small, almost imperceptible variations in performance that aggregate to effect significant long-term damage. Current harmonics generated by a source can pollute the entire power system without being affected itself. The PowerXplorer captures detailed harmonics, interharmonics and subharmonics to effectively troubleshoot the complex problems caused by these events.

