AcuSplitCT Series 4161RSplit Core Current Transformers

The Accuency split core CTs are compact and low-cost current transformers with high accuracy. The CTs are ideal for quick and easy installation without disconnecting cables during installation. Multiple installation mechanisms provide stable and durable current measurement.

FEATURES

- Multiple output including 5A, 1A, 80mA, 100mA, 200mA, 333mV
- Simple hinged installation
- Can be installaed on cable, bus and panel
- Standard Window size from 0.75 to 5 by 7 inch
- Listed to UL2808, 61010-1 and CSA 22.2


SPECIFICATIONS	
Rated Primary Current	Up to 5000A
Rated Output	5A, 1A, 80mA, 100mA, 200mA, 333mV
Withstand Voltage	5,000Vac
Operating Amb. Temperature	-15°C to 65°C
Accuracy	IEC 60044-1 0.5s class
Lead	8 ft(2.5m) UL 1015 22AWG
Construction	UL enclosure rated to 135°C
Certifications	UL listed UL2808, 61010-1 and CSA 22.2

ORDERING INFORMATION

			Rated Input		Rated Output
Ordering Number	AcuCT-4161R	-		-	
Ordering Example	AcuCT-4161R	-	1200	-	333mV
			1200: 1200A		1A
			1600: 1600A		5A
			2000: 2000A		333mV
			2500: 2500A		80mA
			3000: 3000A		100mA
			4000: 4000A		200mA
			5000: 5000A		



DIMENSIONS



SIZE CHART

Dimensions (inch/mm)							
А	A B C		D	E			
7.3/185.0	9.3/235.0	1.8/45.0	4.1/105.0	6.1/155.0			

